



All-in1 Laptop Powerbank 24000

Item no.:

420-57

EAN: 
5705730420573



| | |
|-------------------------------|---------------------|
| 5 Years Warranty | 24000 mAh |
|-------------------------------|---------------------|

| | |
|---|--|
| PD 60W DC 84W USB 22W Fast and Powerful |  Charge multiple devices simultaneously |
|---|--|

| | |
|---|-------------------------------|
|  Charge all USB-C devices | 20V Voltage display |
|---|-------------------------------|

| | |
|---|--|
|  Wireless charger |  Qi-compatible |
|---|--|

| | |
|--|---|
|  Supports Pass-Through Charging DC to USB-C/A 15W |  <input checked="" type="checkbox"/> Carry-On Approved |
|--|---|



| | |
|---|---|
|  |  |
|  |  |
|  |  |

The Sandberg All-in-1 Laptop Powerbank 24000 is your universal energy source on the go for all your mobile equipment, even your laptop or Macbook. With its powerful 24000 mAh battery, there is enough power for several chargings of a smartphone or several hours of extra work on the laptop. The powerbank is simple to recharge with the included AC adapter or from any USB-C charger for a few hours. With the DC outlet and 12 different adapters in the pack, as well as a Quickcharge USB port and two USB-C ports, many different pieces of equipment can be charged at maximum speed. As an added feature, there is even a built-in wireless fast charger on top of the powerbank. The powerbank is easy to bring along in your bag and weighs only 0.5 kg.

 More information:
 www.sandberg.world



Sandberg All-in1 Laptop Powerbank 24000

Specifications

Battery capacity: 24000 mAh (88.8 Wh)
Battery type: Li-Ion
DC-port input: 12-24V/2A (48W Max)
DC-port output: 12V/4A, 16.5V/4A, 20V/4A, 24V/3.5A (84W Max)
USB-C PD input: 5V/3A, 9V/3A, 12V/3A, 15V/3A (45W Max)
USB-C PD output: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/3A (60W Max)
USB-A output: 4.5V/5A, 5V/4.5A, 9V/2A, 12V/1.5A (22W Max)
USB-C (2) output: 5V/3A, 9V/3A, 12V/2.25A (27W Max)
Wireless charger max : 10W
DC and USB-C1 share same circuit: Only one can be active at a time
Simultaneous use: DC output can be used together with USB-C2, USB-A, and wireless charging
Total system limit: Combined output across all ports is limited to approx. 85-90W
Priority: DC output has highest priority; secondary ports may reduce power automatically under high load
Supports Pass-Through Charging: Yes. While DC is input, USB-C2 & USB-A can do output at the same time (15W max per port).
DC5521

Press quotes



Packaging info

1 Sandberg All-In-1 Laptop Powerbank 24000
1 AC charger with EU plug, input AC 110-240V output DC 15V/2A, cable length 1m
1 set of 12 laptop DC plug adaptor tips
1 DC-DC charging cable, 75 cm
1 USB-C to USB-C charging cable, 75 cm
1 Quick guide
1 GPSR Safety guide

Quick guide: <https://sandberg.world/mt/manual/420-57>

Dimensions

| | Product | Package |
|-------------|---------|----------|
| Height (cm) | 12.20 | 22.80 |
| Width (cm) | 12.20 | 25.60 |
| Depth (cm) | 2.65 | 5.90 |
| Weight (g) | 500.00 | 1,100.00 |



Product:
www.sandberg.world/product/all-in-1-laptop-powerbank-2400

Dealer:

