



All-in1 Laptop Powerbank 25000

Atuagaq nr.:

421-46

EAN:



5 Years Warranty	25000 mAh
-------------------------------	---------------------

PD 60W DC 91W USB 18W Fast and powerful	 Charge multiple devices simultaneously
---	---

 Laptop connectors included	24V Voltage display
-----------------------------------	-------------------------------

 Wireless charger	 Qi-compatible
----------------------	-------------------

 Carry-On approved



FC	CE

Sandberg All-in-1 Laptop Powerbank 25000 tassaavoq mobilimik nukissiuutitit – laptopit imaluunniit MacBookit ilanngullugit. 25,000 mAh-nik nukittuunik batteriitaqarami, smartphoneit arlaleriarlugu immiussinnaavat imaluunniit laptopinni sulinissamut akunnerit arlallit amerlanerusut. Powerbanki USB-C imaluunniit DC-in aqqutigalugu sukkasuumik immiunneqarsinnaavoq, USB-C, USB-A aamma DC output-ikkut nukissamik tunisinnaalluni. DC output 12-24 V-mut naleqqussarneqarsinnaavoq, adapterit aqqutigalugit laptopit amerlanerit DC input-illit naleqqussarneqarsinnaallutik, taamaalillutit atortorissaarutit assigiinngitsut amerlasuut nukissamik tunineqarsinnaallutik. Taakkununga ilanngullugu, 15 W-nik wireless fast chargerimik akulerussimasumik smartphoneit kabelimik atornagu immiussinnaavat. Ilusaa mikisuuvoq oqimaassusialu 500 g-iuvoq, powerbanki assanni oqimaatigiisumik inissinneqarsinnaavoq, taamalu angalaaruit, allaffimmiikkuit imaluunniit angalaaruit nukissamik tunineqarnissamut aaqqiissutissatut naleqquttuuvoq.

Paasisaqarnerugit:
 www.sandberg.gl



Sandberg All-in1 Laptop Powerbank 25000

Specifications

Battery capacity: 25000 mAh (91.25 Wh)
Battery type: Li-ion
DC-port input: 12-24V/2A (48W Max)
DC-port output: 12V/6.7A, 15V/4A, 19V/3.8A, 24V/3.8A (91W Max)
USB-C1 input: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/3A (60W Max)
USB-C2 input: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/2.25A (45W Max)
USB-C1 output: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/3A (60W Max)
USB-C2 output: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/2.25A (45W Max)
USB-A output: 5V/3A, 9V/2A, 12V/1.5A (18W Max)
Wireless charger max: 15W

Pass-through charging options:
USB-C2 IN to USB-C1/DC OUT: Max 45W
USB-C1/DC IN to USB-C2 OUT: Max 45W (combined USB-C2+USB-A OUT: Max 15W)
Limitations:
USB-A and USB-C2 share one circuit, max 15W combined use
DC and USB-C1 share one circuit, must be used separately



Emballage paasissutissat

1 Sandberg All-In-1 Laptop Powerbank 24000
1 set of 12 laptop DC plug adaptor tips
1 DC-DC charging cable, 75 cm
1 USB-C to USB-C charging cable, 75 cm
1 Quick guide
1 GPSR Safety guide

Piaartumik ilitsersuut: <https://sandberg.gl/mt/manual/421-46>

Angissutsit

	Nioqqutissaq	Pakke
Angissuseq (cm)	2.65	18.70
Angissuseq (cm)	12.20	23.70
Itissuseq (cm)	12.20	5.50
Oqimaassuseq (g)	500.00	700.00



Nioqqutissaq:
www.sandberg.world/product/all-in1-laptop-powerbank-25000

Tunisassiaq:

