

Sandberg®

Pocket Radio FM+AM Recharge

Artikl br.:

421-02

Sandberg®
ACTIVE

EAN:



5705730421020



Sandberg Pocket Radio FM+AM Recharge je kompaktan i zgodan za poneti sa sobom na aktivnosti na otvorenom. Savršen je za trčanje, vožnju biciklom, kampovanje i sve te vrste aktivnosti. Čak je i idealan radio za hitne slučajeve u slučaju da električna mreža i internet nestanu. Sa ugrađenom punjivom baterijom. Uključene slušalice koje služe kao antena za prijem FM i AM radio signala.



[Više informacija:](#)
 www.sandberg.world

Sandberg Pocket Radio FM+AM Recharge

Specifikacije

AM Frequency range: 522-1710KHz (9KHz) / 520-170KHz (10KHz)
AM Sensitivity: <20mV/m
FM Frequency range: 76-108MHz
AM Signal to noise ratio: >30db
FM Signal to noise ratio: >40db
Maximum output power: 6.5mw
USB-C Input (charging by included USB-A to USB-C cable)
Built-in display
Battery capacity: 500mAh, 3.7V (1.85 Wh)
Playtime: Up to 15hrs



Informacije o pakovanju

1 Sandberg Pocket Radio FM+AM Recharge
1 Earphones
1 Charge cable USB-A to USB-C 50cm
1 Quick guide

Brzi vodič: <https://sandberg.world/mt/manual/421-02>

Dimenzije

	Proizvod	Ambalaža
Visina (cm)	8.60	14.00
Širina (cm)	4.50	10.60
Dubina (cm)	1.20	3.50
Težina (g)	60.00	100.00



Proizvod:

www.sandberg.world/product/pocket-radio-fmam-recharge

Prodavac:

 Sandberg®